Noname manuscript No.
(will be inserted by the editor)

Rapid and Accurate Computation of Whiskered Tori and their Manifolds Near Resonances in Periodically Perturbed Planar Circular Restricted 3-Body Problems

Bhanu Kumar · Rodney L. Anderson · Rafael de la Llave

the date of receipt and acceptance should be inserted later

Abstract When the planar circular restricted 3-body problem (RTBP) is periodically perturbed, families of unstable resonant periodic orbits break up into whiskered tori, with most tori persisting into the perturbed system. In this study, we 1) develop a quasi-Newton method which simultaneously solves for the tori and their center, stable, and unstable directions; 2) implement continuation by both perturbation as well as rotation numbers; 3) compute Fourier-Taylor parameterizations of the stable and unstable manifolds; 4) regularize the equations of motion; and 5) globalize these manifolds. Our methodology improves on efficiency and accuracy compared to prior studies, and applies to a variety of periodic perturbations. We demonstrate the tools on the planar elliptic RTBP.

1 Introduction

Numerous studies have been carried out in recent years where quasi-periodic orbits of various restricted 3-body or 4-body models have been computed and used for applications to space mission design. For instance, Farrés et al. (2017) studied periodic and quasi-periodic orbits in the phase space of the Augmented Hill 3-Body problem near the L_1 and L_2 libration points. Olikara (2016) applied collocation methods to the computation of invariant tori near L_1 and L_2 in both spatial circular restricted 3-body problem (CRTBP) as well as periodically-perturbed planar CRTBP models. And looking slightly further in the past, the book series of Gómez et al. (2001) presented many other computational methods and applications for quasi-periodic orbits near libration points. However, all of these studies, as well as almost all other prior research, use methods which require solving large-dimensional linear systems of equations at each step of the differential correction.

B. Kumar · R. de la Llave
School of Mathematics, Georgia Institute of Technology, 686 Cherry St. NW, Atlanta, GA 30332., USA
E-mail: bkumar30@gatech.edu

R.L. Anderson
Jet Propulsion Laboratory, California Institute of Technology, 4800 Oak Grove Drive, Pasadena, CA 91109

Furthermore, while the quasi-periodic orbits (also known as invariant tori) are computed successfully using those methods, stability information including stable and unstable directions must be computed separately.

Another characteristic of the vast majority of prior research, including the previously mentioned studies, is that the analysis focuses on tori associated with the libration points, such as Lissajous or quasi-halo orbits. Bosanac (2018) did compute invariant tori near stable resonant periodic orbits in the planar circular restricted 3-body problem (PCRTBP), but the tori computed are stable, without stable or unstable manifolds. Unstable resonant periodic orbits and their stable and unstable manifolds are known to be important mechanisms of dynamical transport in the interior and exterior realms of the CRTBP (Koon et al. 2011), and these orbits have seen significant interest and use as a tool for trajectory design in multi-body systems. For example, out of the nine Titan-to-Titan encounters made by Cassini between July 2013 and June 2014, eight of the nine resulting transfers involved resonances (Vaquero et al. 2014). More recently, the baseline mission design for the Europa Lander mission concept made profitable use of these mechanisms for the final approach to the surface of Europa (Anderson et al. 2019). For further examples and more background on resonant orbits, see Anderson et al. (2016).

In this study, we develop efficient algorithms which enable simultaneous computation of not only unstable invariant tori, but also of their center, stable, and unstable directions (also known as bundles) in periodically perturbed PCRTBP models. Solving for bundles as well as tori actually allows us to avoid solving large linear systems, thus improving the algorithmic efficiency of our method compared to tori-only methods used in previous investigations. We apply our tools to the computation of unstable invariant tori and bundles near PCRTBP resonances, with the Jupiter-Europa planar elliptic restricted 3-body problem (PERTBP) used as the dynamical model for demonstration. Next, we use the results of the preceding step to start a recursive parameterization method (Cabré et al. 2005; Huguet et al. 2012; Haro et al. 2016) for the computation of high order Fourier-Taylor approximations of the stable and unstable manifolds of the tori. We demonstrate improvements in manifold accuracy as compared with the linear manifold approximations used in other studies. Finally, we develop a Levi-Civita regularization for the equations of motion, which is used to globalize the parameterized manifolds. We have included several proofs throughout this paper to justify our methods; these may be skipped without detriment by readers primarily interested in details of the algorithm implementation.

2 Models and Background

2.1 Planar Circular Restricted 3-body Problem

In this study, we consider periodic perturbations of the PCRTBP. The PCRTBP considers the motion of an infinitesimally small particle (thought of as a spacecraft) under the gravitational influence of two large bodies of masses m_1 and m_2, collectively referred to as the primaries. In this model, m_1 and m_2 revolve about their barycenter in a circular Keplerian orbit. Units are also normalized so that the distance between the two primaries becomes 1, $\mathcal{G}(m_1+m_2)$ becomes 1, and the primaries' period of revolution becomes 2π. We define a mass ratio $\mu = \frac{m_2}{m_1+m_2}$, and use the usual synodic, rotating non-inertial cartesian coordinate system centered at the barycenter of the primaries such that the two primaries are always on the x-axis. In the planar case we consider here, we also assume that the spacecraft moves in the same plane as the primaries. In this case, the equations of motion are Hamiltonian with form (Celletti 2010)

$$\dot{x} = \frac{\partial H_0}{\partial p_x} \quad \dot{y} = \frac{\partial H_0}{\partial p_y} \qquad \dot{p}_x = -\frac{\partial H_0}{\partial x} \quad \dot{p}_y = -\frac{\partial H_0}{\partial y} \tag{1}$$

$$H_0(x, y, p_x, p_y) = \frac{p_x^2 + p_y^2}{2} + p_x y - p_y x - \frac{1-\mu}{r_1} - \frac{\mu}{r_2} \tag{2}$$

where $r_1 = \sqrt{(x+\mu)^2 + y^2}$ is the distance from the spacecraft to m_1 and $r_2 = \sqrt{(x-1+\mu)^2 + y^2}$ is the distance to m_2.

There are two important properties of Equations (1) and (2) to note. First of all, the Hamiltonian in Eq. (2) is autonomous and is hence an integral of motion. It is related to the well-known Jacobi integral C by $H_0 = -\frac{1}{2}C$. Hence, trajectories in the PCRTBP are restricted to 3-dimensional energy submanifolds of the state space satisfying $H(x, y, p_x, p_y) = \text{constant}$. The second property to note is that the equations of motion have a time-reversal symmetry. Namely, if $(x(t), y(t), t)$ is a solution of Eq. (1) and (2) for $t > 0$, then $(x(-t), -y(-t), t)$ is a solution for $t < 0$.

2.2 Periodic Perturbations of the PCRTBP

The PCRTBP model exhibits many of the important dynamical phenomena present in multi-body celestial systems. However, there are many effects which are not included in the PCRTBP; many of these other influences on the spacecraft motion act in an approximately time-periodic manner, while preserving the Hamiltonian nature of the system. Here we will study dynamical models where one such periodic forcing effect is considered in addition to the PCRTBP. The equations of motion in this case are given by Eq. (3) along with time-periodic Hamiltonian (4)

$$\dot{x} = \frac{\partial H_\varepsilon}{\partial p_x} \quad \dot{y} = \frac{\partial H_\varepsilon}{\partial p_y} \qquad \dot{p}_x = -\frac{\partial H_\varepsilon}{\partial x} \quad \dot{p}_y = -\frac{\partial H_\varepsilon}{\partial y} \qquad \dot{\theta}_p = \Omega_p \tag{3}$$

$$H_\varepsilon(x, y, p_x, p_y, \theta_p) = H_0(x, y, p_x, p_y) + H_1(x, y, p_x, p_y, \theta_p; \varepsilon) \tag{4}$$

where $\theta_p \in \mathbb{T}$ is an angle, H_0 is the PCRTBP Hamiltonian given by Eq. (2), H_1 is the perturbation by the time-periodic effect and satisfies $H_1(x, y, p_x, p_y, \theta_p; 0) = 0$, and $\varepsilon > 0$ and Ω_p are the perturbation parameter and perturbation frequency, respectively. ε signifies the strength of the perturbation, $\varepsilon = 0$ being the unperturbed PCRTBP, and Ω_p is a known constant frequency. The perturbation from H_1 is $2\pi/\Omega_p$ periodic, with θ_p being the phase of the perturbation. Note that the Hamiltonian will no longer be constant along trajectories.

There are many different Hamiltonian periodically perturbed PCRTBP models of interest for applications. A common perturbation added to the PCRTBP is that of a third large body revolving in a circle (or approximate circle) around m_1 or m_2. Examples of these kinds of restricted 4-body models include the bicircular problem (Simó et al. 1995), the coherent quasi-bicircular problem (Andreu 1998), and the Hill restricted 4-body problem (Scheeres 1998). Another common periodically-perturbed PCRTBP model is the planar elliptic restricted 3-body problem (PERTBP), which is described in the following section.

2.3 Planar Elliptic Restricted 3-body Problem

The tools we develop in this paper are applicable to a wide variety of Hamiltonian periodic perturbations as discussed in the previous section. However, in this study, we use the PERTBP for numerical demonstration of their usage. The PERTBP has the same assumptions as the PCRTBP except that one allows m_1 and m_2 to move around their barycenter in an elliptical Keplerian orbit of eccentricity $\varepsilon > 0$. The length unit is normalized such that the semi-major axis of the m_1-m_2 orbit is 1. As the period of the primaries' orbit is 2π, we have that the perturbation frequency $\Omega_p = 1$, so we can consider $\theta_p = t$ modulo 2π.

The PERTBP model we use is essentially the same as that used by Hiday-Johnston and Howell (1994), except for a transformation from position-velocity to position-momentum coordinates and a restriction to the xy-plane. The coordinate system is again such that m_1 and m_2 are always on the x-axis with the origin at their barycenter. However, the distance between them is now time-periodic, with periapse at $t = 0$; this is different from the pulsating coordinates used by Szebehely (1967). The equations of motion are Eq. (3) with time-periodic Hamiltonian

$$H_\varepsilon(x, y, p_x, p_y, t) = \frac{p_x^2 + p_y^2}{2} + n(t)(p_x y - p_y x) - \frac{1-\mu}{r_1} - \frac{\mu}{r_2} \tag{5}$$

where we have $n(t) = \frac{\sqrt{1-\varepsilon^2}}{(1-\varepsilon \cos E(t))^2}$, $r_1 = \sqrt{(x + \mu(1 - \varepsilon \cos E(t)))^2 + y^2}$ and $r_2 = \sqrt{(x - (1-\mu)(1 - \varepsilon \cos E(t)))^2 + y^2}$. $E(t)$ is the 2π-periodic eccentric anomaly of the elliptical m_1-m_2 orbit, and can be computed by solving the standard Kepler's equation (Bate et al. 1971). $n(t)$ is the time derivative of the m_1-m_2 true anomaly. From Eq. (3) and (5), we have $p_x = \dot{x} - n(t)y$ and $p_y = \dot{y} + n(t)x$.

2.4 Resonant Periodic Orbits

Resonant periodic orbits are PCRTBP periodic orbits which, unlike planar Lyapunov orbits, are not in the center manifold of any of the libration points. Their main characteristic is that their orbital periods are nearly rational multiples of 2π, the period of the m_1-m_2 motion (the periods become exact rational multiples of 2π as $\mu \to 0$). A resonance and its corresponding family of periodic orbits is characterized by a ratio $m : n$, $m, n \in \mathbb{Z}^+$. This notation means that in an inertial reference frame, the spacecraft makes approximately m revolutions about m_1 in the time that m_1 and m_2 revolve n times around their barycenter.

For a given resonance $m : n$ in the PCRTBP with $\mu > 0$, there typically exists one stable and one unstable resonant periodic orbit inside the submanifold $H_0(x, y, p_x, p_y) = E$, for each fixed value of E in some interval of energy values $[E_{min}, E_{max}]$ (Kumar et al. 2021a). This gives us continuous families of stable and unstable resonant periodic orbits; the periods of the orbits within a given family vary with E. The unstable resonant periodic orbits have monodromy matrix eigenvalues 1, 1, λ_s, and $\lambda_u = \lambda_s^{-1}$, where $|\lambda_s| < 1$. Thus, there are 2D stable and unstable manifolds attached to the unstable resonant periodic orbits. These manifolds serve as low-energy pathways to and from these periodic orbits. Furthermore, the manifolds of different resonances at the same energy level can intersect in the PCRTBP, giving heteroclinic connections which allow for propellant-free resonance transitions. For more details see Kumar et al. (2021a).

3 Normally Hyperbolic Invariant Manifolds and Existence of Tori

As discussed in Section 2.4, for each value of E in some interval of energy values $[E_{min}, E_{max}]$, there exists one unstable $m : n$ resonant periodic orbit in the PCRTBP. Each of these periodic orbits is diffeomorphic to a circle $\mathbb{T}$. Now, consider the union of all the unstable $m : n$ resonant periodic orbits for all values of $E \in [E_{min}, E_{max}]$. The resulting set is a 2D manifold Ξ diffeomorphic to $\mathbb{T} \times [0, 1]$ in the 4D PCRTBP phase space. Furthermore, at each point of Ξ, there are stable and unstable directions transverse to the manifold, which come from the stable and unstable eigenvectors of the periodic orbits which make up this manifold. The phase space is 4D at each point of Ξ, and Ξ is 2D; hence, at any point of Ξ, we can see that other than the two tangent vectors to the manifold, the stable and unstable directions are the only independent vectors necessary to span the phase space. This means that Ξ is a normally hyperbolic invariant manifold (NHIM) of the PCRTBP flow; similar NHIMs exist for families of planar Lyapunov orbits as well (Capiński et al. 2016). A thorough discussion of NHIMs is outside the scope of this paper, but for rigorous definitions and results for flows, see Fenichel (1971).

One of the most important properties of NHIMs is that they persist under sufficiently small perturbations of the equations of motion (Fenichel 1971); as our numerical results later in this paper will demonstrate, the perturbations we study are indeed sufficiently small. However, to apply this result to our case of time-periodic perturbations, the original and perturbed systems must be defined on the same phase space. Hence, we take the PCRTBP from its original 4D phase space (x, y, p_x, p_y) to the 5D extended phase space $(x, y, p_x, p_y, \theta_p)$, $\theta_p \in \mathbb{T}$. We define $\dot{\theta}_p = \Omega_p$ for the unperturbed PCRTBP in extended phase space, while x, y, p_x, and p_y continue to follow Equations (1) and (2). Hence, periodic orbits of period T_p from the original 4D PCRTBP phase space become 2D quasi-periodic orbits in the PCRTBP defined on the extended phase space, with one of the frequencies being $\Omega_1 = 2\pi/T_p$ and the other being Ω_p, unless Ω_1/Ω_p is rational. The NHIM Ξ from the original phase space becomes the NHIM $\bar{\Xi} = \Xi \times \mathbb{T}$ in the extended phase space due to the extra angle. Hence, $\bar{\Xi}$ is diffeomorphic to $\mathbb{T}^2 \times [0, 1]$.

Now, since the PCRTBP and its NHIM have been transferred to the same extended phase space as the periodically-perturbed models, we can conclude that for $\varepsilon > 0$ sufficiently small, $\bar{\Xi}$ will persist as a NHIM $\bar{\Xi}_\varepsilon$ of the perturbed equations of motion (3) and (4). $\bar{\Xi}_\varepsilon$ will be diffeomorphic to $\bar{\Xi}$ and hence also to $\mathbb{T}^2 \times [0, 1]$. Furthermore, note that $\bar{\Xi}$ in the extended phase space PCRTBP is foliated by 2D invariant tori, since Ξ was foliated by periodic orbits. From KAM theory (Capiński et al. 2016), we can expect that inside $\bar{\Xi}_\varepsilon$, the invariant tori from $\bar{\Xi}$ with sufficiently non-resonant frequencies Ω_1 and Ω_p will also persist after perturbation with only small gaps between them. Hence, we will focus this study on these 2D tori in the periodically-perturbed PCRTBP models.

3.1 Stroboscopic Maps, NHIMs, and Invariant Circles

Any 2D invariant torus in the periodically-perturbed PCRTBP extended phase space can be parameterized as the image of a function of two angles $K_2 : \mathbb{T}^2 \to \mathbb{R}^4 \times \mathbb{T}$. A quasi-periodic trajectory $\mathbf{x}(t)$ lying on this torus can be expressed as

$$\mathbf{x}(t) = K_2(\theta, \theta_p) \qquad \theta = \theta_0 + \Omega_1 t, \quad \theta_p = \theta_{p,0} + \Omega_p t \tag{6}$$

where θ_0 and $\theta_{p,0}$ are determined from the initial condition $\mathbf{x}(0)$, and $\Omega_1 = 2\pi/T_p$, where T_p is the period of the PCRTBP periodic orbit associated with the torus. θ_p is the same perturbation phase angle defined in Section 2.2, so one of the two torus frequencies will be Ω_p. We can then define the stroboscopic map $F_\varepsilon : \mathbb{R}^4 \times \mathbb{T} \to \mathbb{R}^4 \times \mathbb{T}$ as the time-$2\pi/\Omega_p$ mapping of extended phase space points by the equations of motion (3) and (4) with perturbation parameter ε. We find that

$$F_\varepsilon(K_2(\theta, \theta_p)) = K_2(\theta + \omega, \theta_p), \text{ where } \omega = 2\pi\Omega_1/\Omega_p \tag{7}$$

since the angle θ_p advances by 2π in the time $2\pi/\Omega_p$ and is therefore invariant under F_ε. Hence, we can fix θ_p (for our PERTBP test case we choose $\theta_p = 0$), and then define $K(\theta) = K_2(\theta, \theta_p)$. Then, Eq. (7) becomes

$$F_\varepsilon(K(\theta)) = K(\theta + \omega) \tag{8}$$

By ignoring the last fixed θ_p component of the extended phase space and a slight abuse of notation, we can consider $F_\varepsilon : \mathbb{R}^4 \to \mathbb{R}^4$ and $K : \mathbb{T} \to \mathbb{R}^4$.

Eq. (8) implies that K parameterizes an invariant 1D torus of the map F_ε. It is significantly more computationally efficient to compute 1D invariant tori (invariant circles) K of the map F_ε in 4D phase space than 2D tori K_2 of the flow in the 5D extended phase space. The reason for this is that the reduction in the dimension of the torus helps mitigate the curse of dimensionality. Hence, from this point onwards, we will consider the map F_ε and its invariant circles and manifolds, rather than invariant objects of the continuous time flow. Similar approaches are also used by Zhang and de la Llave (2018) and Haro and Mondelo (2021).

As a final remark, the stroboscopic map allows us to use the theory of NHIMs of maps (Fenichel 1971; Hirsch et al. 1977) to understand the presence of invariant circles in periodically-perturbed PCRTBP models. In particular, note that unstable periodic orbits of the unperturbed PCRTBP are also unstable invariant circles of the map $F_{\varepsilon=0}$. Hence, the PCRTBP flow NHIM Ξ defined at the beginning of Section 3 is also a NHIM of the map $F_{\varepsilon=0}$. Just as in the case of flows, the theory shows that NHIMs of maps persist under sufficiently small perturbations of the map. Hence, for sufficiently small $\varepsilon > 0$, we can expect that Ξ will persist as a NHIM Ξ_ε of F_ε, with Ξ_ε diffeomorphic to Ξ and hence also to $\mathbb{T} \times [0, 1]$. Furthermore, since Ξ is foliated by invariant circles whose rotation numbers satisfy a twist condition, KAM theory (Capiński et al. 2016) tells us that that the invariant circles with sufficiently irrational rotation number ω persist inside Ξ_ε for $\varepsilon > 0$.

4 A Parameterization Method for Computing Invariant Tori and Bundles

In this section, we develop and implement a parameterization method for the simultaneous computation of unstable invariant tori as well as their center, stable, and unstable directions, also known as bundles, for stroboscopic maps of periodically-perturbed PCRTBP models. We present the analytical details and derivation of the method, as well as the considerations required for its discretization and numerical implementation in a computer program. The method is broadly inspired by the methods of Haro et al. (2016), except for the additional presence of a center bundle which is not considered by them and requires additional calculations. A computationally different but conceptually related method can also be found in the work of Fontich et al. (2009).

4.1 The Parameterization Method for Invariant Manifolds

The parameterization method is a general technique for the computation of many kinds of invariant objects in dynamical systems, including tori and stable and unstable manifolds. Haro et al. (2016) describe several applications. The idea is that given a map $F : \mathbb{R}^d \to \mathbb{R}^d$, if we know that there is an F-invariant object diffeomorphic to some model manifold $\mathcal{M}$, then we can solve for a function $W : \mathcal{M} \to \mathbb{R}^d$ and a diffeomorphism $f : \mathcal{M} \to \mathcal{M}$ such that the invariance equation

$$F(W(s)) = W(f(s)) \tag{9}$$

holds for all $s \in \mathcal{M}$. W is referred to as the parameterization of the invariant manifold, and f as the internal dynamics on $\mathcal{M}$. Eq. (9) means that F maps the image $W(\mathcal{M})$ into itself, so that $W(\mathcal{M})$ is the invariant object in the full space $\mathbb{R}^d$.

4.2 Equations for Parameterization Method for Tori and Bundles

For notational convenience, denote the stroboscopic map F_ε from Section 3.1 as F from now on. We assume that the rotation number $\omega = 2\pi\Omega_1/\Omega_p$ is known for the invariant circle we are trying to compute; this is the case whenever the circle comes from a PCRTBP periodic orbit of known period T_p and hence known $\Omega_1 = 2\pi/T_p$. As given in Eq. (8), we wish to find a parameterization $K : \mathbb{T} \to \mathbb{R}^4$ of the F-invariant circle satisfying the torus invariance equation

$$F(K(\theta)) = K(\theta + \omega) \tag{10}$$

This is equivalent to the framework of Section 4.1 with $\mathcal{M} = \mathbb{T}$ and $f(s) = s + \omega$. In addition, for our quasi-Newton method, we will add another equation to be solved for matrix-valued periodic functions $P(\theta)$, $\Lambda(\theta) : \mathbb{T} \to \mathbb{R}^{4\times 4}$ such that

$$DF(K(\theta))P(\theta) = P(\theta + \omega)\Lambda(\theta) \tag{11}$$

Furthermore, we mandate that $\Lambda(\theta)$ has the form

$$\Lambda(\theta) = \begin{bmatrix} 1 & T(\theta) & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & \lambda_s(\theta) & 0 \\ 0 & 0 & 0 & \lambda_u(\theta) \end{bmatrix} \tag{12}$$

for some functions $T(\theta), \lambda_s(\theta), \lambda_u(\theta) : \mathbb{T} \to \mathbb{R}$ to be solved for. The form of Eq. (12) is motivated by geometric considerations that we will detail in Section 4.3.

As will be explained at the end of Section 4.5, solving simultaneously for K, P, and Λ is actually more efficient than solving for K alone; the quasi-Newton method we will present for solving Eq. (10)-(11) uses the near-diagonal form of Λ to decouple the linear system of equations we get in each differential correction step. The method will require only algebraic operations, phase shifts, and the solving of 1D equations for scalar-valued functions.

4.3 Understanding the P and Λ Matrices

In addition to their numerical utility, P and Λ have a geometric significance which will be useful when computing stable and unstable manifolds later on. Since K is contained in the 2D normally hyperbolic invariant manifold Ξ_ε defined at the end of Section (3.1), we know that there are tangent, center, stable, and unstable directions to the torus at each point $K(\theta)$. The columns of P will be these four vector bundles, with $\lambda_s(\theta)$ and $\lambda_u(\theta)$ set to the stable and unstable multipliers for the corresponding bundles. To see why, consider Eq. (11) column by column.

Let $\mathbf{v}_t(\theta), \mathbf{v}_c(\theta)$, $\mathbf{v}_s(\theta)$, and $\mathbf{v}_u(\theta)$ denote the first, second, third, and fourth columns of $P(\theta)$, respectively. Then, Equations (11) and (12) are equivalent to

$$DF(K(\theta))\mathbf{v}_t(\theta) = \mathbf{v}_t(\theta+\omega) \tag{13}$$
$$DF(K(\theta))\mathbf{v}_c(\theta) = T(\theta)DK(\theta+\omega) + \mathbf{v}_c(\theta+\omega) \tag{14}$$
$$DF(K(\theta))\mathbf{v}_s(\theta) = \lambda_s(\theta)\mathbf{v}_s(\theta+\omega) \tag{15}$$
$$DF(K(\theta))\mathbf{v}_u(\theta) = \lambda_u(\theta)\mathbf{v}_u(\theta+\omega) \tag{16}$$

First of all, note that Eq. (15)-(16) are the definition of stable and unstable bundles $\mathbf{v}_s(\theta)$ and $\mathbf{v}_u(\theta)$ and multipliers $\lambda_s(\theta)$ and $\lambda_u(\theta)$ for the torus K. Hence, the third and fourth columns of P satisfy Eq. (11) if and only if they are torus stable and unstable bundles, respectively. Also, differentiating Eq. (10) gives

$$DF(K(\theta))DK(\theta) = DK(\theta+\omega) \tag{17}$$

which shows that $\mathbf{v}_t(\theta) = DK(\theta)$ solves Eq. (13). As a result, the first column of P can be set as the torus tangent bundle $DK(\theta)$; in fact, if Eq. (11) has a solution, it is easy to show that column 1 of P *must* be $\alpha DK(\theta)$ for some $\alpha \in \mathbb{R}$.

Finally, since F is a Hamiltonian flow map and hence is symplectic, given $K(\theta)$, $\mathbf{v}_s(\theta)$, and $\mathbf{v}_u(\theta)$, we can find $\mathbf{v}_c(\theta)$ solving Eq. (14) for some function $T : \mathbb{T} \to \mathbb{R}$; we postpone the description and proof of how to compute such a $\mathbf{v}_c(\theta)$ to Section 4.8 where the method will be used. Any such $\mathbf{v}_c(\theta)$ is known as a symplectic conjugate to $DK(\theta)$, and is a center direction to the torus K (de la Llave et al. 2005). Hence, column 2 of P satisfies Eq. (11) if and only if it is a symplectic conjugate center bundle. We should note that Eq. (11) is actually underdetermined; symplectic conjugates are not unique, and we can change the scales of the stable and unstable bundles; we will take advantage of this in Section 4.7 to make Λ constant.

4.4 Summary of Steps for Quasi Newton-Method

We will now develop our quasi-Newton method for solving Eq. (10) and (11). Before presenting the details of the method, we give a brief overview. Assume we have an approximate solution (K, P, Λ) for Eq. (10)-(11). Then, we will

1. Compute $E(\theta) = F(K(\theta)) - K(\theta+\omega)$, $E_{red}(\theta) = P^{-1}(\theta+\omega)DF(K(\theta))P(\theta) - \Lambda(\theta)$
2. Solve $-P^{-1}(\theta+\omega)E(\theta) = \Lambda(\theta)\xi(\theta) - \xi(\theta+\omega)$ for $\xi : \mathbb{T} \to \mathbb{R}^4$ using Eq. (23)-(26) and set $K(\theta)$ equal to $K(\theta) + P(\theta)\xi(\theta)$ (details given in Section 4.5).
3. Set column 1 of $P(\theta)$ to $DK(\theta)$. Recompute $DF(K(\theta))$ and $E_{red}(\theta)$.
4. Solve $-E_{red}(\theta) = \Lambda(\theta)Q(\theta) - Q(\theta+\omega)\Lambda(\theta) - \Delta\Lambda(\theta)$ for $Q : \mathbb{T} \to \mathbb{R}^{4\times 4}$ and $\Delta\Lambda$ using Eq. (37)-(48). Set $P(\theta)$ equal to $P(\theta) + P(\theta)Q(\theta)$ and $\Lambda(\theta)$ equal to $\Lambda(\theta) + \Delta\Lambda(\theta)$ (details given in Section 4.6).
5. Return to step 1 and repeat correction until E and E_{red} are within tolerance.

4.5 Quasi-Newton Step for Correcting K

We seek to solve Eq. (10) and (11) for K, P, and Λ. All the entries of Λ are fixed as 0 or 1 as shown in Eq. (12) except for $T(\theta)$, $\lambda_s(\theta)$, and $\lambda_u(\theta)$. We will now derive an iterative step that, given an approximate solution (K, P, Λ) of Eq. (10) and (11), produces a much more accurate one. Define the errors

$$E(\theta) = F(K(\theta)) - K(\theta + \omega) \tag{18}$$

$$E_{red}(\theta) = P^{-1}(\theta + \omega) DF(K(\theta)) P(\theta) - \Lambda(\theta) \tag{19}$$

We then need to find corrections ΔK, ΔP, and $\Delta\Lambda$ to cancel E and E_{red}. We start with ΔK; write $\Delta K(\theta) = P(\theta)\xi(\theta)$. We will solve for $\xi : \mathbb{T} \to \mathbb{R}^4$ satisfying

$$\eta(\theta) \stackrel{\text{def}}{=} -P^{-1}(\theta + \omega)E(\theta) = \Lambda(\theta)\xi(\theta) - \xi(\theta + \omega) \tag{20}$$

Claim For ω sufficiently irrational and E and E_{red} sufficiently small, if ξ solves Eq. (20), then adding $\Delta K = P\xi$ to K reduces the error E quadratically.

Remark 1 We use the phrase "sufficiently irrational" when describing conditions on ω that ensure the validity of our quasi-Newton method. For those aware of KAM theory, what we mean by this is that ω must be Diophantine, as most numbers are (Huguet et al. 2012). This condition arises due to the classic small-divisors problem of KAM theory when solving cohomological equations (see Eq. (30)).

Proof Substitute $K(\theta) + \Delta K(\theta)$ into the RHS of Eq. (18). Assuming that ΔK is small enough (true if E is sufficiently small), we can expand in Taylor series to get

$$\begin{aligned} E_{new}(\theta) &= F(K(\theta) + \Delta K(\theta)) - [K(\theta + \omega) + \Delta K(\theta + \omega)] \\ &= F(K(\theta)) + DF(K(\theta))\Delta K(\theta) + O(\Delta K(\theta)^2) - [K(\theta + \omega) + \Delta K(\theta + \omega)] \\ &= E(\theta) + DF(K(\theta))\Delta K(\theta) - \Delta K(\theta + \omega) + O(\Delta K(\theta)^2) \end{aligned} \tag{21}$$

$\Delta K = P\xi$, and Eq. (19) implies $DF(K(\theta))P(\theta) = P(\theta + \omega)\left[\Lambda(\theta) + E_{red}(\theta)\right]$. Thus,

$$\begin{aligned} E_{new}(\theta) &= E(\theta) + DF(K(\theta))P(\theta)\xi(\theta) - P(\theta + \omega)\xi(\theta + \omega) + O(\xi(\theta)^2) \\ &= E(\theta) + P(\theta + \omega)\left[\Lambda(\theta)\xi(\theta) + E_{red}(\theta)\xi(\theta) - \xi(\theta + \omega)\right] + O(\xi(\theta)^2) \\ &= P(\theta + \omega)E_{red}(\theta)\xi(\theta) + O(\xi(\theta)^2) \end{aligned} \tag{22}$$

where the last line follows from Eq. (20). For ω sufficiently irrational, ξ will be similar in magnitude to E, so $E_{red}(\theta)\xi(\theta)$ will be quadratically small like $E_{red}(\theta)E(\theta)$. Hence, as long as E (and hence ξ and ΔK) are small enough that the Taylor expansion in Eq. (71) is valid, and the $O(\xi^2)$ terms of the Taylor expansion are small, the new error E_{new} will be quadratically smaller than E. □

To solve Eq. (20), let $\xi(\theta) = \begin{bmatrix}\xi_1 \ \xi_2 \ \xi_3 \ \xi_4\end{bmatrix}^T$ and $\eta_(\theta) = \begin{bmatrix}\eta_1 \ \eta_2 \ \eta_3 \ \eta_4\end{bmatrix}^T$. As Λ is nearly diagonal, we can write Eq. (20) component-wise as

$$\eta_1(\theta) - T(\theta)\xi_2(\theta) = \xi_1(\theta) - \xi_1(\theta + \omega) \tag{23}$$

$$\eta_2(\theta) = \xi_2(\theta) - \xi_2(\theta + \omega) \tag{24}$$

$$\eta_3(\theta) = \lambda_s(\theta)\xi_3(\theta) - \xi_3(\theta + \omega) \tag{25}$$

$$\eta_4(\theta) = \lambda_u(\theta)\xi_4(\theta) - \xi_4(\theta + \omega) \tag{26}$$

4.5.1 Fixed-Point Iteration: Solving for ξ_3 and ξ_4

To solve for ξ_3 and ξ_4, rewrite Equations (25) and (26) in the form

$$\xi_3(\theta) = \lambda_s(\theta - \omega)\xi_3(\theta - \omega) - \eta_3(\theta - \omega) \stackrel{\text{def}}{=} [A(\xi_3)](\theta) \tag{27}$$

$$\xi_4(\theta) = \lambda_u^{-1}(\theta)\,[\eta_4(\theta) + \xi_4(\theta + \omega)] \stackrel{\text{def}}{=} [B(\xi_4)](\theta) \tag{28}$$

We define A as a map from functions to functions, which sends any $f(\theta) : \mathbb{T} \to \mathbb{R}$ to the new function $[A(f)](\theta) = \lambda_s(\theta-\omega)f(\theta-\omega) - \eta_3(\theta-\omega)$; B is defined similarly using Eq. (28). To find ξ_3 and ξ_4, let $\xi_{3,0} = \xi_{4,0} = 0$ and iterate $\xi_{3,n+1} = A(\xi_{3,n})$ and $\xi_{4,n+1} = B(\xi_{4,n})$ repeatedly, starting at $n = 0$. The iterations will converge to the desired solutions ξ_3 and ξ_4 of Eq. (27) and (28). We now explain why.

Lemma 1 *A and B are contraction maps, and the iterations $\xi_{3,n+1} = A(\xi_{3,n})$ and $\xi_{4,n+1} = B(\xi_{4,n})$ converge exponentially fast as $n \to \infty$ to the solutions ξ_3 and ξ_4.*

Proof Note that $|\lambda_s(\theta)| < 1$ and $|\lambda_u^{-1}(\theta)| < 1$ for all $\theta \in \mathbb{T}$. Let $f_1, f_2 : \mathbb{T} \to \mathbb{R}$ be two continuous functions, and define $C = \max_{\theta\in\mathbb{T}} |\lambda_s(\theta)| < 1$. We have that

$$\begin{aligned} &\max_{\theta\in\mathbb{T}} \|[A(f_1)](\theta) - [A(f_2)](\theta)\| \\ &\qquad = \max_{\theta\in\mathbb{T}} \|\lambda_s(\theta-\omega)f_1(\theta-\omega) - \lambda_s(\theta-\omega)f_2(\theta-\omega)\| \\ &\qquad \leq C \max_{\theta\in\mathbb{T}} \|f_1(\theta-\omega) - f_2(\theta-\omega)\| = C \max_{\theta\in\mathbb{T}} \|f_1(\theta) - f_2(\theta)\| \end{aligned} \tag{29}$$

As $C < 1$, A is a contraction map under the uniform norm; the same can be shown for B very similarly. The contraction mapping theorem (Chicone 2006) tells us that every such map has a unique fixed point; furthermore, the fixed point can be found by iterating any value in the domain of the map forwards until convergence. The solutions of Equations (27) and (28) are by definition the fixed points of contraction maps A and B. Hence, the iterations converge to ξ_3 and ξ_4. □

Remark 2 If λ_s and λ_u are constant, Fourier methods (see Section 4.5.2) can also be used to solve Eq. (25) and (26). We did not ensure constant λ_s and λ_u in our implementation of the algorithm, hence the use of fixed-point iteration instead.

4.5.2 Cohomological Equations: Solving for ξ_1 and ξ_2

We next solve Eq. (24) for ξ_2, which is then used in the LHS of Eq. (23) to solve for ξ_1. In both cases, we must solve cohomological equations of form

$$b(\theta) = a(\theta) - a(\theta + \omega) \tag{30}$$

where b is known and a is not. This can easily be solved by Fourier series; let $\hat{a}(k)$ and $\hat{b}(k)$ be the kth Fourier coefficients of a and b. Then, Eq. (30) becomes

$$\sum_{k\in\mathbb{Z}} \hat{b}(k)e^{jk\theta} = \sum_{k\in\mathbb{Z}} \hat{a}(k)e^{jk\theta} - \sum_{k\in\mathbb{Z}} \hat{a}(k)e^{jk(\theta+\omega)} = \sum_{k\in\mathbb{Z}} \hat{a}(k)(1 - e^{jk\omega})e^{jk\theta} \tag{31}$$

where $j = \sqrt{-1}$. Then, for ω sufficiently irrational, setting $\hat{a}(k) = \hat{b}(k)(1 - e^{jk\omega})^{-1}$ allows us to compute $a(\theta)$ except for $\hat{a}(0)$. In the $k = 0$ case, $\hat{a}(0)$ cancels out on the right hand side of Eq. (30) and can hence take any value, making the solution a non-unique. Furthermore, we observe that a necessary condition for the existence of a solution is $\hat{b}(0) = 0$. $\hat{a}(0)$ and $\hat{b}(0)$ are simply the averages of a and b on $\mathbb{T}$.

We first solve Eq. (24) for $\hat{\xi}_2(k)$, $k \neq 0$, using the Fourier series method. To set $\hat{\xi}_2(0)$, first find the average α of $\eta_1 - T \times [\xi_2 - \hat{\xi}_2(0)]$. Then, choose $\hat{\xi}_2(0) = \alpha/\hat{T}(0)$, so that the LHS of Eq. (23) has zero average when solving for ξ_1. With ξ_2 fully solved, we then solve Eq. (23) for $\hat{\xi}_1(k)$, $k \neq 0$ and arbitrarily choose $\hat{\xi}_1(0) = 0$. Finally, with all four components of ξ solved, we set $K(\theta)$ equal to $K(\theta) + P(\theta)\xi(\theta)$, concluding the K correction part of the quasi-Newton step.

In practice, when solving Eq. (24) for ξ_2, we find that the average of $\eta_2(\theta)$, the left hand side of Eq. (24), is not exactly zero; we ignore this nonzero average and solve for the $\hat{\xi}_2(k)$ anyways as described earlier. $\hat{\eta}_2(0)$ decreases to zero with each quasi-Newton step as the method converges, so we are able to solve Eq. (24) more exactly; this occurs (Fontich et al. 2009) as F is an exact symplectic map, since it is a fixed-time map of a Hamiltonian system on $\mathbb{R}^4$ (Golé 2001). Also, for those familiar with the parameterization method for invariant tori, note that the choice of $\hat{\xi}_1(0) = 0$ takes care of the translation non-uniqueness of solutions of Eq. (10) without requiring extra constraint equations.

Remark 3 There are methods of numerically solving for ΔK without using P or Λ, including single-shooting (Farrés et al. 2017) and collocation (Olikara 2016) methods. These methods effectively discretize θ on a grid of N points and solve a linearized version of Eq. (71) directly for ΔK at those θ values. This requires solving at least a $4N$ dimensional linear system at each correction step. Gaussian elimination applied to this will hence have a computational complexity of $O(N^3)$. However, by using P and the nearly diagonal Λ, we decouple the equations and avoid this large dimensional system. The complexity of our quasi-Newton method is $O(N \log N)$ (as some steps use FFT). Furthermore, our method gives us not just K, but also the bundle and Floquet matrices P and Λ.

4.6 Quasi-Newton Step for Correcting P and Λ

Using the newly computed $K(\theta)$, we set the first column of $P(\theta)$ to $DK(\theta)$, and then recompute $DF(K(\theta))$ and $E_{red}(\theta)$ using Eq. (19). Finding $\Delta P(\theta)$ and $\Delta\Lambda(\theta)$ to cancel E_{red} then follows similar methodology as ΔK. Let $\Delta P(\theta) = P(\theta)Q(\theta)$; we will solve for Q and $\Delta\Lambda : \mathbb{T} \to \mathbb{R}^{4\times 4}$ satisfying

$$-E_{red}(\theta) = \Lambda(\theta)Q(\theta) - Q(\theta+\omega)\Lambda(\theta) - \Delta\Lambda(\theta) \tag{32}$$

Claim For ω sufficiently irrational and E_{red} sufficiently small, if Q and $\Delta\Lambda$ solve Eq. (32), then adding $\Delta P = PQ$ to P and $\Delta\Lambda$ to Λ reduces E_{red} quadratically.

Proof Substitute $P + PQ$ and $\Lambda + \Delta\Lambda$ into Eq. (11) to define

$$\begin{aligned}\mathcal{E}(\theta) = DF(K(\theta))[P(\theta) + P(\theta)Q(\theta)]\\ - [P(\theta+\omega) + P(\theta+\omega)Q(\theta+\omega)][\Lambda(\theta) + \Delta\Lambda(\theta)]\end{aligned} \tag{33}$$

Using $E_{red}(\theta) = P^{-1}(\theta+\omega)DF(K(\theta))P(\theta) - \Lambda(\theta)$, we then find that

$$\begin{aligned}
P(\theta+\omega)^{-1}\mathcal{E}(\theta) &= E_{red}(\theta) + P(\theta+\omega)^{-1}DF(K(\theta))P(\theta)Q(\theta) \\
&\qquad - Q(\theta+\omega)[\Lambda(\theta)+\Delta\Lambda(\theta)] - \Delta\Lambda(\theta) \\
&= E_{red}(\theta) + [\Lambda(\theta)+E_{red}(\theta)]Q(\theta) - Q(\theta+\omega)[\Lambda(\theta)+\Delta\Lambda(\theta)] - \Delta\Lambda(\theta) \\
&= E_{red}(\theta)Q(\theta) - Q(\theta+\omega)\Delta\Lambda(\theta)
\end{aligned} \tag{34}$$

where the last line follows due to Eq. (32). Evaluating Eq. (19) with $P+PQ$ and $\Lambda+\Delta\Lambda$ in place of P and Λ and denoting the result as $E_{red,new}$, we have

$$\begin{aligned}
E_{red,new}(\theta) &= [P(\theta+\omega)+P(\theta+\omega)Q(\theta+\omega)]^{-1}\mathcal{E}(\theta) \\
&= [I+Q(\theta+\omega)]^{-1}P(\theta+\omega)^{-1}\mathcal{E}(\theta) \\
&= [I+Q(\theta+\omega)]^{-1}[E_{red}(\theta)Q(\theta) - Q(\theta+\omega)\Delta\Lambda(\theta)]
\end{aligned} \tag{35}$$

Now, for ω sufficiently irrational, Q and $\Delta\Lambda$ will be similar in magnitude to E_{red}. Hence, if E_{red} is small, then $E_{red,new}$ will be quadratically smaller like E_{red}^2. □

Since Λ is nearly diagonal, the equations for the different entries of Q and $\Delta\Lambda$ following from Eq. (32) are almost completely decoupled from each other. Write

$$\begin{gathered}
E_{red}(\theta) = \begin{bmatrix} E_{LL}(\theta) & E_{LC}(\theta) & E_{LS}(\theta) & E_{LU}(\theta) \\ E_{CL}(\theta) & E_{CC}(\theta) & E_{CS}(\theta) & E_{CU}(\theta) \\ E_{SL}(\theta) & E_{SC}(\theta) & E_{SS}(\theta) & E_{SU}(\theta) \\ E_{UL}(\theta) & E_{UC}(\theta) & E_{US}(\theta) & E_{UU}(\theta) \end{bmatrix} \\
Q(\theta) = \begin{bmatrix} 0 & Q_{LC}(\theta) & Q_{LS}(\theta) & Q_{LU}(\theta) \\ 0 & Q_{CC}(\theta) & Q_{CS}(\theta) & Q_{CU}(\theta) \\ 0 & Q_{SC}(\theta) & Q_{SS}(\theta) & Q_{SU}(\theta) \\ 0 & Q_{UC}(\theta) & Q_{US}(\theta) & Q_{UU}(\theta) \end{bmatrix} \quad \Delta\Lambda(\theta) = \begin{bmatrix} 0 & \Delta T(\theta) & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & \Delta\lambda_s(\theta) & 0 \\ 0 & 0 & 0 & \Delta\lambda_u(\theta) \end{bmatrix}
\end{gathered} \tag{36}$$

As the first column of $P(\theta)$ is fixed to be $DK(\theta)$, we fix the first column of $Q(\theta)$ to be zero so that the first column of ΔP is zero as well. We can then write columns 2-4 of Eq. (32) entry by entry to get 12 scalar equations

$$-E_{LC}(\theta) - T(\theta)Q_{CC}(\theta) = Q_{LC}(\theta) - Q_{LC}(\theta+\omega) - \Delta T(\theta) \tag{37}$$
$$-E_{LS}(\theta) - T(\theta)Q_{CS}(\theta) = Q_{LS}(\theta) - \lambda_s(\theta)Q_{LS}(\theta+\omega) \tag{38}$$
$$-E_{LU}(\theta) - T(\theta)Q_{CU}(\theta) = Q_{LU}(\theta) - \lambda_u(\theta)Q_{LU}(\theta+\omega) \tag{39}$$
$$-E_{CC}(\theta) = Q_{CC}(\theta) - Q_{CC}(\theta+\omega) \tag{40}$$
$$-E_{CS}(\theta) = Q_{CS}(\theta) - \lambda_s(\theta)Q_{CS}(\theta+\omega) \tag{41}$$
$$-E_{CU}(\theta) = Q_{CU}(\theta) - \lambda_u(\theta)Q_{CU}(\theta+\omega) \tag{42}$$
$$-E_{SC}(\theta) = \lambda_s(\theta)Q_{SC}(\theta) - Q_{SC}(\theta+\omega) \tag{43}$$
$$-E_{SS}(\theta) = \lambda_s(\theta)Q_{SS}(\theta) - \lambda_s(\theta)Q_{SS}(\theta+\omega) - \Delta\lambda_s(\theta) \tag{44}$$
$$-E_{SU}(\theta) = \lambda_s(\theta)Q_{SU}(\theta) - \lambda_u(\theta)Q_{SU}(\theta+\omega) \tag{45}$$
$$-E_{UC}(\theta) = \lambda_u(\theta)Q_{UC}(\theta) - Q_{UC}(\theta+\omega) \tag{46}$$
$$-E_{US}(\theta) = \lambda_u(\theta)Q_{US}(\theta) - \lambda_s(\theta)Q_{US}(\theta+\omega) \tag{47}$$
$$-E_{UU}(\theta) = \lambda_u(\theta)Q_{UU}(\theta) - \lambda_u(\theta)Q_{UU}(\theta+\omega) - \Delta\lambda_u(\theta) \tag{48}$$

First, we solve Equations (41), (42), (43), (45), (46), and (47), followed by Eq. (38) and (39) (after back substitution), using the exact same method that was used to solve Eq. (25) and (26); rearrange each equation so that its solution is the fixed point of an appropriately defined contraction map, which is then iterated to convergence. Such maps always multiply their input by either λ_s or λ_u^{-1}, or both. Eq. (40) is solved using the Fourier series method which was described in Section 4.5.2; we arbitrarily choose the average of the solution $\hat{Q}_{CC}(0) = 0$. We ignore the nonzero average of E_{CC}, which goes to zero as the quasi-Newton method converges due to F being exact symplectic. Finally, the solutions to Eq. (37), (44), and (48) are non-unique; we choose $Q_{LC} = Q_{SS} = Q_{UU} = 0$, so that we have $\Delta T(\theta) = E_{LC}(\theta) + T(\theta)Q_{CC}(\theta)$, $\Delta\lambda_s(\theta) = E_{SS}(\theta)$, and $\Delta\lambda_u(\theta) = E_{UU}(\theta)$.

Once Q and $\Delta\Lambda$ are known, we set $P(\theta)$ equal to $P(\theta) + P(\theta)Q(\theta)$, $\Lambda(\theta)$ equal to $\Lambda(\theta) + \Delta\Lambda(\theta)$, and then recompute $E(\theta)$ and $E_{red}(\theta)$ using Eq. (18) and (19). Finally, we go back to the quasi-Newton step for correcting the circle parameterization $K(\theta)$ and repeat the entire method until E and E_{red} are within tolerance.

Remark 4 If T, λ_s, and λ_u are constant, we can choose the non-unique solutions of Eq. (37), (44), and (48) such that this property is preserved. In particular, choose ΔT, $\Delta\lambda_s$, and $\Delta\lambda_u$ as the (constant) averages of E_{LC}, E_{SS} and E_{UU}, respectively, and solve for Q_{LC}, Q_{SS}, and Q_{UU} using the Fourier methods of Section 4.5.2.

4.7 Modifying P for Constant Λ

Let K, P, and Λ be a solution to Eq. (10) and Eq. (11). For purposes of numerical stability as well as stable/unstable manifold computation (see Section 5), it can be useful to modify the second, third, and fourth columns of P in such a way that $\Lambda = P^{-1}(\theta+\omega)DF(K(\theta))P(\theta)$ becomes a constant matrix of the form in Eq. (12), i.e. $T(\theta)$, $\lambda_s(\theta)$, and $\lambda_u(\theta)$ become constant. For columns 3 and 4 of P, the stable and unstable bundles $\mathbf{v}_s(\theta)$ and $\mathbf{v}_u(\theta)$, respectively, just a simple rescaling is needed. Let $\bar{\lambda}_s, \bar{\lambda}_u \in \mathbb{R}$ and $a_s, a_u : \mathbb{T} \to \mathbb{R}$ be the solutions to

$$\log(\lambda_s(\theta)) - \log(\bar{\lambda}_s) = \log(a_s(\theta+\omega)) - \log(a_s(\theta)) \tag{49}$$

$$\log(\lambda_u(\theta)) - \log(\bar{\lambda}_u) = \log(a_u(\theta+\omega)) - \log(a_u(\theta)) \tag{50}$$

We choose $\bar{\lambda}_s = \exp\left[\frac{1}{2\pi}\int_0^{2\pi}\log(\lambda_s(\theta))\,d\theta\right]$ so the LHS of Eq. (49) has zero average. Letting $u(\theta) = \log(a_s(\theta))$, Eq. (49) becomes a cohomological equation of form Eq. (30) which can be solved for u by the Fourier series method; we choose $\hat{u}(0) = 0$. This gives $a_s(\theta) = e^{u(\theta)}$. We can solve Eq. (50) for $a_u(\theta)$ in the exact same manner. Finally, one can replace columns 3 and 4 of P by $a_s(\theta)\mathbf{v}_s(\theta)$ and $a_u(\theta)\mathbf{v}_u(\theta)$, and replace $\lambda_s(\theta)$ and $\lambda_u(\theta)$ in Λ by $\bar{\lambda}_s$ and $\bar{\lambda}_u$. We prove that this works now.

Lemma 2 *If $\mathbf{v}_s(\theta)$ and $\mathbf{v}_u(\theta)$ satisfy Eq.* (15)-(16)*, and $a_s(\theta)$ and $a_u(\theta)$ satisfy Eq.* (49)-(50)*, then $\mathbf{v}_{s,new}(\theta) = a_s(\theta)\mathbf{v}_s(\theta)$ and $\mathbf{v}_{u,new}(\theta) = a_u(\theta)\mathbf{v}_u(\theta)$ satisfy*

$$DF(K(\theta))\mathbf{v}_{s,new}(\theta) = \bar{\lambda}_s\mathbf{v}_{s,new}(\theta+\omega) \tag{51}$$

$$DF(K(\theta))\mathbf{v}_{u,new}(\theta) = \bar{\lambda}_u\mathbf{v}_{u,new}(\theta+\omega) \tag{52}$$

Proof We prove the result for $\mathbf{v}_{s,new}$; the case of $\mathbf{v}_{u,new}$ can be proven in the exact same manner. Since $\mathbf{v}_s(\theta)$ satisfies Eq. (15), we have

$$\begin{aligned} DF(K(\theta))\mathbf{v}_{s,new}(\theta) &= DF(K(\theta))a_s(\theta)\mathbf{v}_s(\theta) = a_s(\theta)\lambda_s(\theta)\mathbf{v}_s(\theta+\omega) \\ &= a_s(\theta+\omega)\bar{\lambda}_s\mathbf{v}_s(\theta+\omega) = \bar{\lambda}_s\mathbf{v}_{s,new}(\theta+\omega) \end{aligned} \tag{53}$$

where $a_s(\theta)\lambda_s(\theta) = a_s(\theta+\omega)\bar{\lambda}_s$ follows from exponentiating Eq. (49). □

We can also modify the second column of P, the symplectic conjugate center direction $\mathbf{v}_c(\theta)$, to make $T(\theta)$ constant. This is possible because as mentioned in Section 4.3, the symplectic conjugate is not unique; given $a : \mathbb{T} \to \mathbb{R}$ and $\mathbf{v}_c(\theta)$ satisfying Eq. (14), the function $\mathbf{v}_c(\theta)+a(\theta)DK(\theta)$ also solves Eq. (14) except with a change in $T(\theta)$ (which was anyways arbitrary). Hence, we choose $a(\theta)$ which kills all variation of $T(\theta)$ about its average $\hat{T}(0)$. The equation for this is:

$$-\left(T(\theta) - \hat{T}(0)\right) = a(\theta) - a(\theta+\omega) \tag{54}$$

which can be solved using the Fourier series method given for Eq. (30). Then, one simply adds $a(\theta)DK(\theta)$ to column 2 of P and replaces $T(\theta)$ with $\hat{T}(0)$ in Λ. Note that the LHS of Eq. (54) has average zero, so a solution $a(\theta)$ can be found.

Lemma 3 *If $\mathbf{v}_c(\theta)$ and $a(\theta)$ satisfy Eq.* (14) *and* (54)*, respectively, then the function $\mathbf{v}_{c,new}(\theta) = \mathbf{v}_c(\theta) + a(\theta)DK(\theta)$ is also a symplectic conjugate and satisfies*

$$DF(K(\theta))\mathbf{v}_{c,new}(\theta) = \hat{T}(0)DK(\theta+\omega) + \mathbf{v}_{c,new}(\theta+\omega) \tag{55}$$

Proof Since $\mathbf{v}_c(\theta)$ satisfies Eq. (14) and $DK(\theta)$ satisfies Eq. (17), we have

$$\begin{aligned} DF(K(\theta))\mathbf{v}_{c,new}(\theta) &= DF(K(\theta))\left[\mathbf{v}_c(\theta) + a(\theta)DK(\theta)\right] \\ &= \left[T(\theta) + a(\theta)\right]DK(\theta+\omega) + \mathbf{v}_c(\theta+\omega) \\ &= \left[\hat{T}(0) + a(\theta+\omega)\right]DK(\theta+\omega) + \mathbf{v}_c(\theta+\omega) \\ &= \hat{T}(0)DK(\theta+\omega) + \mathbf{v}_{c,new}(\theta+\omega) \end{aligned} \tag{56}$$

where the relation $T(\theta) + a(\theta) = \hat{T}(0) + a(\theta+\omega)$ follows from Eq. (54). □

4.8 Initialization for Continuation by ε

To compute invariant circles and bundles of stroboscopic maps in periodically-perturbed PCRTBP models with some desired perturbation parameter $\varepsilon_f > 0$, we start from periodic orbits and their bundles in the unperturbed PCRTBP ($\varepsilon = 0$) and continue by ε until the torus and bundles for $\varepsilon = \varepsilon_f$ are found. Our quasi-Newton method-based continuation follows the standard procedure; choose a number of continuation steps n, take an invariant circle and bundles from the $\varepsilon = 0$ system, and use them as an initial guess for the quasi-Newton method to solve for the circle and bundles in the $\varepsilon = \varepsilon_f/n$ system. Similarly, for $i = 0, \ldots, n-1$, use the solution from the $\varepsilon_f i/n$ system as an initial guess for the solution in the $\varepsilon_f(i+1)/n$ system. Once $i = n-1$, we have the torus and bundles for $\varepsilon = \varepsilon_f$. We need to find the $\varepsilon = 0$ solution to initialize the continuation, however.

To get $K(\theta)$, $P(\theta)$, and $\Lambda(\theta)$ solving Eq. (10) and (11) for the $\varepsilon = 0$ PCRTBP case, one needs to first choose a periodic orbit which is to be continued (recall that PCRTBP periodic orbits are also invariant circles of the stroboscopic map $F = F_{\varepsilon=0}$, unless the orbit period is resonant with $2\pi/\Omega_p$). From this periodic orbit, we get its period T_p and hence the rotation number $\omega = 4\pi^2/(T_p\Omega_p)$, as well as a point $\mathbf{x}_0$ lying on the orbit. Let $\phi(\mathbf{x}, t)$ denote the time-t map of the point $\mathbf{x} \in \mathbb{R}^4$ by the PCRTBP equations of motion. Then, we can take $K(\theta) = \phi(\mathbf{x}_0, T_p\frac{\theta}{2\pi})$ if the periodic orbit monodromy matrix stable and unstable eigenvalues are positive. If they are negative, though, a "double covering" trick needs be used so that $P(\theta)$ can be continuously defined. For this, set $K(\theta) = \phi(\mathbf{x}_0, 2T_p\frac{\theta}{2\pi})$ and $\omega = 2\pi^2/(T_p\Omega_p)$ so that K sweeps over the periodic orbit twice as θ goes from 0 to 2π. In either case, it is easy to verify that $K(\theta)$ satisfies Eq. (10).

Next, set the first column of $P(\theta)$ to be $DK(\theta)$, and set the third and fourth columns of $P(\theta)$ as the stable and unstable unit eigenvectors of the periodic orbit monodromy matrix at the point $K(\theta)$. Denote these stable and unstable eigenvectors as $\mathbf{v}_s(\theta)$ and $\mathbf{v}_u(\theta)$, respectively. One needs to make sure that the directions of $\mathbf{v}_s(\theta)$ and $\mathbf{v}_u(\theta)$ at each point $K(\theta)$ are chosen such that they are continuously oriented functions of θ; this is always possible if K is defined as previously described. Finally, finding the second column of P requires some extra calculations.

As mentioned in Section 4.3, the second column of P represents the symplectic conjugate direction to $DK(\theta)$ and is part of the center bundle. The first step in its computation is to compute $\lambda_s(\theta)$ and $\lambda_u(\theta) : \mathbb{T} \to \mathbb{R}$ such that

$$DF(K(\theta))\mathbf{v}_s(\theta) = \lambda_s(\theta)\mathbf{v}_s(\theta + \omega) \tag{57}$$

$$DF(K(\theta))\mathbf{v}_u(\theta) = \lambda_u(\theta)\mathbf{v}_u(\theta + \omega) \tag{58}$$

which can be done since $DF(K(\theta))$ maps the stable and unstable bundles into themselves. Next, find functions $A(\theta), B(\theta), C(\theta)$, and $D(\theta) : \mathbb{T} \to \mathbb{R}$ such that

$$\begin{aligned} DF(K(\theta))\frac{J^{-1}DK(\theta)}{\|DK(\theta)\|^2} = A(\theta)DK(\theta+\omega) + B(\theta)\frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2} \\ + C(\theta)\mathbf{v}_s(\theta+\omega) + D(\theta)\mathbf{v}_u(\theta+\omega) \end{aligned} \tag{59}$$

where $J = \begin{bmatrix} 0_{2\times2} & I_{2\times2} \\ -I_{2\times2} & 0_{2\times2} \end{bmatrix}$ is the 4×4 matrix of the symplectic form in the usual Euclidean metric on $\mathbb{R}^4$. All the quantities in (59) are known except for A, B, C, and D, which can hence be solved for as a system of linear equations. One will find that $B(\theta) = 1$; this occurs as a result of symplectic geometric considerations (see Eq. (68)). After this, we solve for functions $f_1(\theta), f_2(\theta) : \mathbb{T} \to \mathbb{R}$ such that

$$C(\theta) = f_1(\theta + \omega) - \lambda_s(\theta)f_1(\theta) \tag{60}$$

$$D(\theta) = f_2(\theta + \omega) - \lambda_u(\theta)f_2(\theta) \tag{61}$$

which can be done using the same contraction map iteration method used to solve Equations (25) and (26) in Section 4.5.1. Finally, we can express the second column of $P(\theta)$, the symplectic conjugate direction $\mathbf{v}_c(\theta)$, as

$$\mathbf{v}_c(\theta) = \frac{J^{-1}DK(\theta)}{\|DK(\theta)\|^2} + f_1(\theta)\mathbf{v}_s(\theta) + f_2(\theta)\mathbf{v}_u(\theta) \tag{62}$$

With $P(\theta)$ known, to find Λ one can simply use $\Lambda(\theta) = P^{-1}(\theta+\omega)DF(K(\theta))P(\theta)$, after which we can start the continuation. As long as the previous steps were followed correctly, Λ will be of the form given in Eq. (12). To see this, recall the discussion in Section 4.3, and note that the first, third, and fourth columns of P satisfy Equations (13), (15), and (16). Hence, we just need to show that the second column of P satisfies Eq. (14). We prove this now.

Lemma 4 *For some $T : \mathbb{T} \to \mathbb{R}$. the function $\mathbf{v}_c(\theta)$ defined in Eq. (62) satisfies*

$$DF(K(\theta))\mathbf{v}_c(\theta) = T(\theta)DK(\theta+\omega) + \mathbf{v}_c(\theta+\omega) \tag{63}$$

Proof Applying Eq. (62) and then Equations (57), (58), and (59), we have

$$\begin{aligned} DF(K(\theta))\mathbf{v}_c(\theta) = DF(K(\theta)) &\left(\frac{J^{-1}DK(\theta)}{\|DK(\theta)\|^2} + f_1(\theta)\mathbf{v}_s(\theta) + f_2(\theta)\mathbf{v}_u(\theta)\right) \\ =& A(\theta)DK(\theta+\omega) + B(\theta)\frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2} \\ &+ \left(C(\theta) + \lambda_s(\theta)f_1(\theta)\right)\mathbf{v}_s(\theta+\omega) + \left(D(\theta) + \lambda_u(\theta)f_2(\theta)\right)\mathbf{v}_u(\theta+\omega) \end{aligned} \tag{64}$$

Recalling Equations (60) and (61), we thus have that

$$\begin{aligned} DF(K(\theta))\mathbf{v}_c(\theta) =& A(\theta)DK(\theta+\omega) + B(\theta)\frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2} \\ &+ f_1(\theta+\omega)\mathbf{v}_s(\theta+\omega) + f_2(\theta+\omega)\mathbf{v}_u(\theta+\omega) \end{aligned} \tag{65}$$

Flow maps of Hamiltonian systems are symplectic (Thirring 1992). Hence, F satisfies $\Omega(\mathbf{v}_1, \mathbf{v}_2) = \Omega(DF(K(\theta))\mathbf{v}_1, DF(K(\theta))\mathbf{v}_2)$ for all $\mathbf{v}_1,\ \mathbf{v}_2 \in \mathbb{R}^4$, where Ω is the bilinear symplectic form defined on Euclidean $\mathbb{R}^4$ as $\Omega(\mathbf{v}_1, \mathbf{v}_2) = \mathbf{v}_1^T J\mathbf{v}_2$. It is easy to see that $\Omega(\mathbf{v}_1, \mathbf{v}_1) = 0$ for any $\mathbf{v}_1 \in \mathbb{R}^4$. Furthermore, defining $L = \max_{\theta\in\mathbb{T}} |\lambda_s(\theta)| < 1$ and recalling equations (17) and (57), we have that

$$\begin{aligned} \max_{\theta\in\mathbb{T}} |\Omega(DK(\theta), \mathbf{v}_s(\theta))| &= \max_{\theta\in\mathbb{T}} |\Omega\left(DF(K(\theta))DK(\theta), DF(K(\theta))\mathbf{v}_s(\theta)\right)| \\ &= \max_{\theta\in\mathbb{T}} |\Omega\left(DK(\theta+\omega), \lambda_s(\theta)\mathbf{v}_s(\theta+\omega)\right)| \\ &= \max_{\theta\in\mathbb{T}} |\lambda_s(\theta)|\,|\Omega\left(DK(\theta+\omega), \mathbf{v}_s(\theta+\omega)\right)| \\ &\le L\max_{\theta\in\mathbb{T}} |\Omega\left(DK(\theta+\omega), \mathbf{v}_s(\theta+\omega)\right)| = L\max_{\theta\in\mathbb{T}} |\Omega\left(DK(\theta), \mathbf{v}_s(\theta)\right)| \end{aligned} \tag{66}$$

which implies that $\max_{\theta\in\mathbb{T}} |\Omega\left(DK(\theta), \mathbf{v}_s(\theta)\right)| = 0$ since $0 < L < 1$. Thus, for all $\theta \in \mathbb{T}$, $\Omega\left(DK(\theta), \mathbf{v}_s(\theta)\right) = 0$. We can also show that $\Omega\left(DK(\theta), \mathbf{v}_u(\theta)\right) = 0$ in a very similar manner to Eq. (66). Hence, using Eq. (62) for $\mathbf{v}_c$, we find

$$\begin{aligned} \Omega(DK(\theta), \mathbf{v}_c(\theta)) &= \Omega\left(DK(\theta), \frac{J^{-1}DK(\theta)}{\|DK(\theta)\|^2} + f_1(\theta)\mathbf{v}_s(\theta) + f_2(\theta)\mathbf{v}_u(\theta)\right) \\ &= \Omega\left(DK(\theta), \frac{J^{-1}DK(\theta)}{\|DK(\theta)\|^2}\right) \\ &= DK(\theta)^T J\frac{J^{-1}DK(\theta)}{\|DK(\theta)\|^2} = \frac{DK(\theta)^T DK(\theta)}{\|DK(\theta)\|^2} = 1 \end{aligned} \tag{67}$$

Since F is a symplectic map, using Eq. (65) we have that

$$\begin{aligned}
1 &= \Omega(DK(\theta), \mathbf{v}_c(\theta)) \\
&= \Omega\left(DF(K(\theta))DK(\theta), DF(K(\theta))\mathbf{v}_c(\theta)\right) \\
&= \Omega\Bigg(DK(\theta+\omega), A(\theta)DK(\theta+\omega) + B(\theta)\frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2} \\
&\qquad\qquad + f_1(\theta+\omega)\mathbf{v}_s(\theta+\omega) + f_2(\theta+\omega)\mathbf{v}_u(\theta+\omega)\Bigg) \qquad (68) \\
&= \Omega\left(DK(\theta+\omega), B(\theta)\frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2}\right) \\
&= B(\theta)DK(\theta+\omega)^T J \frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2} = B(\theta)
\end{aligned}$$

proving that $B(\theta) = 1$. Therefore, substituting this into Eq. (65) gives

$$\begin{aligned}
DF(K(\theta))\mathbf{v}_c(\theta) =& A(\theta)DK(\theta+\omega) + \frac{J^{-1}DK(\theta+\omega)}{\|DK(\theta+\omega)\|^2} \\
&+ f_1(\theta+\omega)\mathbf{v}_s(\theta+\omega) + f_2(\theta+\omega)\mathbf{v}_u(\theta+\omega)
\end{aligned} \qquad (69)$$

Finally, we see from Eq. (62) that the last 3 terms on the RHS are precisely $\mathbf{v}_c(\theta+\omega)$. Letting $T(\theta) = A(\theta)$, we hence conclude that

$$DF(K(\theta))\mathbf{v}_c(\theta) = T(\theta)DK(\theta+\omega) + \mathbf{v}_c(\theta+\omega) \qquad (70)$$

which is what we sought to prove. □

4.9 Computing Families of Tori: Continuation by ω

The continuation by ε described in Section 4.8 is carried out with ω fixed. However, in the PCRTBP, periodic orbits occur in one-parameter families, with varying rotation numbers ω under $F_{\varepsilon=0}$. The same is true of invariant circles of F_ε for $\varepsilon = \varepsilon_f > 0$ as well. To compute the family of F_{ε_f}-invariant tori corresponding to a PCRTBP periodic orbit family, one option is to continue several different periodic orbits from that family (corresponding to different ω values) by ε. However, this is inefficient, as the tori and bundles computed for $\varepsilon < \varepsilon_f$ are not of interest. Instead, it is better to first compute just one invariant circle of F_{ε_f}, along with its bundles, at some rotation number $\omega = \omega_0$ using continuation by ε. After this, one can continue the ω_0 circle/bundles by ω, with $\varepsilon = \varepsilon_f$ fixed. The continuation by ω is quite similar to the continuation by ε; given a known exact solution to Eq. (10) and (11) for $\omega = \omega_i$, $i \in \mathbb{Z}$, one uses this to form an initial guess for the quasi-Newton method to compute the torus/bundles for $\omega = \omega_{i+1} = \omega_i + \Delta\omega_i$. This recursively gives us tori for a range of ω values. The $\Delta\omega_i$ are called the continuation step sizes.

One can use the torus and bundles for $\omega = \omega_i$ directly as an initial guess for $\omega = \omega_i + \Delta\omega_i$. However, it is extremely easy to use K, P, and Λ from ω_i to compute a better initial guess for the $\omega_i + \Delta\omega_i$ torus, which aids in quasi-Newton method convergence. Assume that Λ has constant $T(\theta) = T$ (apply the procedure from Section 4.7 to P and Λ if necessary). Then, using $\mathbf{v}_c(\theta)$ to denote column 2 of P, the initial guess for the $\omega_i + \Delta\omega_i$ torus parameterization should be $K_{new}(\theta) = K(\theta) + (\Delta\omega_i/T)\mathbf{v}_c(\theta)$. We justify this now.

Claim If K, P, and Λ (with Λ constant) solve Eq. (10)-(11) for $\omega = \omega_i$, then $K_{new}(\theta) = K(\theta) + (\Delta\omega_i/T)\mathbf{v}_c(\theta)$ solves Eq. (10) for $\omega = \omega_i + \Delta\omega_i$ up to $O(\Delta\omega_i^2)$.

Proof For notational convenience, write ω and $\Delta\omega$ in place of ω_i and $\Delta\omega_i$, respectively. Then, evaluating $F(K_{new}(\theta)) - K_{new}(\theta + \omega + \Delta\omega)$, we find this equals

$$
\begin{aligned}
&F\left(K(\theta) + \frac{\Delta\omega}{T}\mathbf{v}_c(\theta)\right) - \left[K(\theta + \omega + \Delta\omega) + \frac{\Delta\omega}{T}\mathbf{v}_c(\theta + \omega + \Delta\omega)\right] \\
&\quad = F(K(\theta)) + DF(K(\theta))\frac{\Delta\omega}{T}\mathbf{v}_c(\theta) + O(\Delta\omega^2) \\
&\qquad\qquad - \left[K(\theta + \omega) + \Delta\omega DK(\theta + \omega) + \frac{\Delta\omega}{T}\mathbf{v}_c(\theta + \omega) + O(\Delta\omega^2)\right] \\
&\quad = \frac{\Delta\omega}{T}\left[DF(K(\theta))\mathbf{v}_c(\theta) - T\,DK(\theta + \omega) - \mathbf{v}_c(\theta + \omega)\right] + O(\Delta\omega^2) = O(\Delta\omega^2)
\end{aligned} \tag{71}
$$

where the last equality follows from Eq. (14). □

Remark 5 Using the Poincaré-Lindstedt method, it is possible to get higher order expansions in $\Delta\omega_i$ for K_{new} than the linear approximation $K(\theta) + (\Delta\omega_i/T)\mathbf{v}_c(\theta)$. This requires significant extra computations which we decided not to carry out.

There is one more difference between continuation by ω and continuation by ε. The continuation by ε uses a fixed step size ε_f/n. However, for continuation by ω, the step size $\Delta\omega_i$ must be varied due to quasi-Newton method divergence for insufficiently irrational ω. At such ω values, the PCRTBP invariant circle breaks down after the perturbation $\varepsilon = \varepsilon_f$, leading to a gap between tori at smaller and larger rotation numbers. Our continuation needs to "jump" over this gap. Suppose we have a torus and bundles for $\omega = \omega_i$, and let φ_i denote the largest of $\Delta\omega_{i-1}, \Delta\omega_{i-2}, \dots, \Delta\omega_{i-5}$. It is natural to try $\Delta\omega_i = \varphi_i$. If the quasi-Newton method diverges for $\omega = \omega_i + \varphi_i$, however, then instead one can try $\Delta\omega_i = \varphi_i/2$; if this still does not work, try $\Delta\omega_i = \varphi_i/2^2$, and so on until we find a $\Delta\omega_i$ that works. Once we have the circle/bundles for $\omega_{i+1} = \omega_i + \Delta\omega_i$, we repeat the process.

In this procedure, it is possible for $\Delta\omega_{i+1}$ to be larger than $\Delta\omega_i$, which is what allows us to "jump" over gaps in the tori. For example, suppose that $\Delta\omega_{i-1}$ through $\Delta\omega_{i-5}$ are all equal to $\phi = \frac{1+\sqrt{5}}{2} \times 10^{-4}$, so $\varphi_i = \phi$. Then, it can happen that the quasi-Newton method diverges for $\omega = \omega_i + \phi$, but converges for $\omega = \omega_i + \phi/2 = \omega_{i+1}$, so $\Delta\omega_i = \phi/2$. However, φ_{i+1} will still equal ϕ, so we try $\Delta\omega_{i+1} = \phi$. If the quasi-Newton method converges for $\omega = \omega_{i+1} + \phi = \omega_i + 3\phi/2$, then we will have crossed the torus gap encountered earlier at $\omega = \omega_i + \phi$. This is schematically illustrated in Figure 1; we draw the tori on a projection of the 2D cylindrical NHIM Ξ_ε defined in Section 3.1 (we let (θ, I) be coordinates on Ξ_ε).

4.10 Discretization and Implementation

When implementing the previously-described methods on a computer, it is necessary to discretize all the functions used as well as the operations on them. We represent K, P, Λ, and other functions of θ as arrays of their values on a discrete grid of N evenly spaced θ values $\theta_i = 2\pi i/N$, $i = 0, \dots, N-1$. Many operations on functions can be carried out element-wise on these arrays; such operations include